

Shure BETA 87A Vokal Mikrofon



Shure BETA 87A Vokal Mikrofon TEKNİK ÖZELLİKLER

Transducer Type : Condenser
Polar Pattern: Supercardioid
Frequency Response: 50 Hz - 20 kHz
Sensitivity (1 kHz): -52,5 dBV/Pa / 2,37 mV/Pa
Equivalent Selfnoise: 23,5 dB(A)
Sound Pressure: 140,5 dB
Weight: 207 g