

Shure BETA 87C Vokal Mikrofon



Shure BETA 87C Vokal Mikrofon TEKNİK ÖZELLİKLER

Transducer Type : Condenser
Polar Pattern: Cardioid
Frequency Response: 50 Hz - 20 kHz
Sensitivity (1 kHz): -51 dBV/Pa / 2,8 mV/Pa
Equivalent Selfnoise: 22 dB(A)
Sound Pressure: 139 dB
Weight: 207 g